



ECHO SERIES

Radio Remote Controls



Emergency Stop



LED Indicator Lights



Ergonomic Comfort



Impact Resistant Shell



Variable Voltage Receiver



Receiving Status Indication



STARKEAMERICA.COM



S601 Series



S802 Series

Kit Options

SKU	Control Type	Motions	Speeds	Kits Include	Receiver Power Supply	Transmitter Power Supply	Frequency
S601-SP-3M	Standard	3	1	1 Receiver & 2 Handheld Transmitters	24V-264V AC/DC	(2) AA Batteries	433 MHz
S601-2P-2M	Dual Hoist & Trolley Festoonless	2 + A/B Both Controls	1	2 Receivers & 2 Handheld Transmitters	24V-264V AC/DC	(2) AA Batteries	433 MHz
S802-SP-3M	Standard	3	2	1 Receiver & 2 Handheld Transmitters	24V-264V AC/DC	(2) AA Batteries	433 MHz
S802-SP-4M	Standard	4	2	1 Receiver & 2 Handheld Transmitters	24V-264V AC/DC	(2) AA Batteries	433 MHz
S802-1P-3M	Single Hoist Festoonless	3 + A/B Both Controls	2	2 Receivers & 2 Handheld Transmitters	24V-264V AC/DC	(2) AA Batteries	433 MHz
S802-2P-3M	Dual Hoist & Trolley Festoonless	3 + A/B Both Controls	2	3 Receivers & 2 Handheld Transmitters	24V-264V AC/DC	(2) AA Batteries	433 MHz

Technical Data

Transmitter		Receiver	
Frequency Range	255 Channel Options 425MHz ~ 474MHz	Frequency Range	255 Channel Options a425MHz ~ 474MHz
Typical Operating Range	328 ft	Sensitivity	-112dBm@baud1.2k bps
Typical Response Time	50mS ~ 100mS	Typical Response Time	50 mS ~ 100 mS
Average Power Consumption	16mA@DC3V (default setting)	Standby Power	16mA@AC220V
Radio – Frequency Power	<10dBm (default setting)	Operating Temperature	-31 F - 176 F
Operating Temperature	-31 F - 176 F	Enclosure Rating	Nema 4 / IP65
Enclosure Rating	Nema 4 / IP65	Housing Material	PA6 (30% GF)
Housing Material	PA6 (30% GF)		

